Trimble R12i GNSS SYSTEM

++++++++++++++++++







- Challenging GNSS environments are locations where the receiver has sufficient satellite availability to achieve minimum accuracy requirements, but where the signal may be partly obstructed by and/or reflected off of trees, buildings, and other objects. Actual results may vary based on user's geographic location and atmospheric activity, scintillation levels, GNSS constellation health and availability, and level of multipath and signal occlusion.

 The current capability in the receivers is based on publicly available information. As such, Trimble cannot guarantee that these receivers will be fully compatible with a future generation of Galileo satellites or signals.

 Precision and reliability may be subject to anomalies due to multipath, obstructions, satellite geometry, and atmospheric conditions. The specifications stated recommend the use of stable mounts in an open sky view, EMI and multipath clean environment, optimal GNSS constellation configurations, along with the use of survey practices that are generally accepted for performing the highest-order surveys for the applicable application including occupation times appropriate for baseline length. Baselines longer than 30 km require precise ephemeris and occupations up to 24 hours may be required to achieve the high precision static specification.

 Network RTK PPM values are referenced to the closest physical base station.
- 24 nours may be required to achieve the high precision static specification.

 Network RTIK PPM values are referenced to the closest physical base station.

 May be affected by atmospheric conditions, signal multipath, obstructions and satellite geometry. Initialization reliability is continuously monitored to ensure highest quality.

 TIP references the overall positioning error estimate at the tip of the surveying pole throughout the tilt compensation range. RTIK refers to the estimated horizontal precision of the underlying GNSS position, which is dependent on factors that affect GNSS solution quality. The 5 mm constant error component accounts for residual misalignment between the vertical axes of the receiver and the built-in inertial Measurement Unit (IMU) after factory calibration, assuming the precisive is mounted on a standard? On earthy fiftee range note which is properly calibrated and free between the vertical axes of in the receiver and in the bulletin fine dia Measurement of the (Micro) after factory calibrated and free from physical defects. The tilt-dependent error component is a function of the quality of the computed tilt azimuth which is assumed here to be aligned using optimal GNSS conditions.

 RMS performance based on repeatable in field measurements. Achievable accuracy and initialization time may
- vary based on type and capability of receiver and antenna, user's geographic location and atmospheric activity scintillation levels, GNSS constellation health and availability and level of multipath including obstructions such as
- scintiliation levels, whose constellation nealth and availability and level or multipath including obstructions such as large trees and buildings.

 Accuracies are dependent on GNSS satellite availability. xFill positioning without an xFill Premium subscription ends after 5 minutes of radio downtime. xFill Premium will continue beyond 5 minutes providing the solution has converged, with typical precisions not exceeding 3 cm horizontal, 7 cm vertical. xFill is not available in all regions, check with your local sales representative for more information.
- 9 RTK refers to the last reported precision before the correction source was lost and xFill started.
- 18 Receiver will operate normally to ~40 °C, internal batteries are rated from ~20 °C to +60 °C (ambient +50 °C).

 12 Tracking GPS, GLONASS and SBAS satellites.

 13 Varies with temperature and wireless data rate. When using a receiver and internal radio in the transmit mode, it is recommended that an external 6 Ah or higher battery is used.
- 14 Varies with terrain and operating conditions. 15 Due to local regulations, the integrated cellular modem cannot be enabled in China, Taiwan, or Brazil. A Trimble controller integrated cellular modem or external cellular modem can be used to obtain GNSS corrections via an (Internet Protocol) connection.

 16 Bluetooth type approvals are country specific.

Specifications subject to change without notice.











NORTH AMERICA Trimble Inc.

10368 Westmoor Dr Westminster CO 80021

Trimble Germany GmbH Am Prime Parc 11 65479 Raunheim #13-02 HarbourFront Tower Two Singapore 099254

ASIA-PACIFIC Trimble Navigation Singapore PTE Limited 3 HarbourFront Place

© 2020, Trimble Inc. All rights reserved. Trimble, the Globe & Triangle logo, CenterPoint, and xFill are trademarks of Trimble Inc., registered in the United States and in other countries. Access, ProPoint, SiteVision, TIP, Trimble RTX and VRS are trademarks of Trimble Inc. iPad and iPhone are trademarks of Apple Inc., registered in the U.S. and other countries. Google, Google Play, and other marks are trademarks of Google LLC. Wi-Fi is a registered trademark of Wi-Fi Alliance. The Bluetooth word mark and logos are owned by the Bluetooth SIG, Inc. and any use of such marks by Trimble Inc. is under license. Galileo is developed under a License of the European Union and the European Space Agency. All other trademarks are the property of their res



DATASHEET

Trimble R12i

GNSS SYSTEM

KEY FEATURES

- Trimble® Inertial Platform™ (TIP) technology. Calibration-free and magnetically immune IMU-based tilt compensation for topo measurements and stakeout.
- ► Trimble ProPoint™ GNSS positioning engine. Engineered for improved accuracy and productivity in challenging GNSS conditions.
- ► 672-channel solution with Trimble 360 satellite tracking technology
- ► CenterPoint® RTX correction service delivers fast, RTK level accuracy worldwide via satellite/IP
- ► Trimble xFill® correction outage technology
- Doptimized for Trimble Access[™] field software
- ► Android[™] and iOS platform support
- ► Cellular, Bluetooth®, Wi-Fi data connectivity
- Military-spec rugged design and IP-67 rating
- ► Ergonomic form factor
- ► All day battery with built-in status indicator
- ► 6 GB internal memory
- ► Supports augmented reality capabilities through Trimble SiteVision™

geospatial.trimble.com/R12i



++++++++++++++++









PERFORMANCE SPECIFICATIONS			
GNSS MEASUREMENTS			
	Constellation agnostic, flexible signal tracking, improved positioning in challenging environments¹ and inertial measureme integration with Trimble ProPoint GNSS technology. Increased measurement and stakeout productivity and traceability with Trimble TIP™ technology IMU-based tilt compensation		
	Advanced Trimble Custom Survey GNSS chips with 672 channels Reduced downtime due to loss of radio signal or cellular connectivity with Trimble xFill technology		
	Signals tracked simultaneously	GPS: L1C, L1C/A, L2C, L2E, L5 GLONASS: L1C/A, L1P, L2C/A, L2P, L3 SBAS (WAAS, EGNOS, GAGAN, MSAS): L1C/A, L5 Galileo: E1, E5A, E5B, E5 AltBOC, E6² BeiDou: B1, B1C, B2, B2A, B2B, B3 QZSS: L1C/A, L1S, L1C, L2C, L5, L6 NavIC (IRNSS): L5 L-band: Trimble RTX™ Corrections	
	Iridium filtering above 1616 MHz allows antenna to be used up to 20 m away from iridium transmitter Japanese LTE filtering below 1510 MHz allows antenna to be used up to 100 m away from Japanese LTE cell tower		
	Digital Signal Processor (DSP) techniques to detect and recover from spoofed GNSS signals Advanced Receiver Autonomous Integrity Monitoring (RAIM) algorithm to detect and reject problem satellite measureme to improve position quality Improved protection from erroneous ephemeris data		
	Positioning Rates	1 Hz, 2 Hz, 5 Hz, 10 Hz, and 20 Hz	
POSITIONING PERFORMANC	E ³		
STATIC GNSS SURVEYING			
High-Precision Static			
Tilgit i Tecisioti Static	Horizontal	3 mm + 0.1 ppm RMS	
	Vertical	3.5 mm + 0.4 ppm RMS	
Ctatic and Foot Ctati-	vertical	э.э пин т о.н рринкию	
Static and Fast Static	Horizontal	3 mm + 0.5 ppm RMS	
		* *	
DEAL TIME KINES ATTO OLD TO	Vertical	5 mm + 0.5 ppm RMS	
REAL TIME KINEMATIC SURVEYIN Single Baseline <30 km			
	Horizontal	8 mm + 1 ppm RMS	
	Vertical	15 mm + 1 ppm RMS	
Network RTK ⁴			
	Horizontal	8 mm + 0.5 ppm RMS	
	Vertical	15 mm + 0.5 ppm RMS	
RTK start-up time for specified precisions ⁵		2 to 8 seconds	
TRIMBLE INERTIAL PLATFORM (T	IP) TECHNOLOGY		
TIP Compensated Surveying ⁶			
	Horizontal	RTK + 5 mm + 0.4 mm/° tilt (up to 30°) RMS	
	Horizontal	RTX + 5 mm + 0.4 mm/° tilt (up to 30°) RMS	
IMU Integrity Monitor	Bias monitoring	Temperature, age and shock	
TRIMBLE RTX CORRECTION SERV	/ICES		
CenterPoint RTX ⁷			
	Horizontal	2 cm RMS	
	Vertical	5 cm RMS	
	RTX convergence time for specified precisions in Trimble RTX Fast regions	<1min	
	RTX convergence time for specified precisions in non RTX Fast regions RTX QuickStart convergence time for specified precisions	<15 min <1 min	
TRIMBLE xFILL8	With Quienotal t convergence time for specified precisions	*411001	
INIVIDLE XFILL	Horizontal	RTK ⁹ + 10 mm/minute RMS	
	Vertical	RTK ⁹ + 20 mm/minute RMS	
TOWARD F WELL DREAM IN 40	vertical	NTN + 20 HIII/HIIIIule NWS	
TRIMBLE xFILL PREMIUM ⁸	Harizantal	2 om PMC	
	Horizontal	3 cm RMS	
	Vertical	7 cm RMS	
CODE DIFFERENTIAL GNSS POSIT			
	Horizontal	0.25 m + 1 ppm RMS	
	Vertical	0.50 m + 1 ppm RMS	
	SBAS ¹⁰	typically <5 m 3DRMS	

Trimble R12i GNSS SYSTEM

HARDWARE			
PHYSICAL			
Dimensions (W×H)	11.9 cm x 13.6 cm (4.6 in x 5.4 in)		
, , ,	1.12 kg (2.49 lb) with internal battery, internal radio with UHF antenna,		
Weight	3.95 kg (8.71 lb) items above plus range pole, Trimble TSC7 controller & bracket		
Temperature ¹¹			
	Operating	-40 °C to +65 °C (-40 °F to +149 °F)	
	Storage	-40 °C to +75 °C (-40 °F to +167 °F)	
Humidity		100%, condensing	
Ingress protection		IP67 dustproof, protected from temporary immersion to depth of 1 m (3.28 ft)	
Shock and vibration (Tested and meets the following environmental standards)			
	Shock	Non-operating: Designed to survive a 2 m (6.6 ft) pole drop onto concrete. Operating: to 40 G, 10 msec, sawtooth	
	Vibration	MIL-STD-810F, FIG.514.5C-1	
ELECTRICAL			
	Power 11 to 24 V DC external power input with over-voltage protection on Port 1 and Port 2 (7-pin Lemo) Rechargeable, removable 7.4 V, 3.7 Ah Lithium-ion smart battery with LED status indicators Power consumption is 4.2 W in RTK rover mode with internal radio ¹²		
Operating times on internal battery ¹³			
	450 MHz receive only option	6.5 hours	
	450 MHz receive/transmit option (0.5 W)	6.0 hours	
	450 MHz receive/transmit option (2.0 W)	5.5 hours	
	Cellular receive option	6.5 hours	
COMMUNICATIONS AND DATAS	STORAGE		
Serial	3-wire serial (7-pin Lemo)		
USB v2.0	Supports data download and high speed communications		
Radio modem	Fully Integrated, sealed 450 MHz wide band receiver/transmitter with frequency range of 403 MHz to 473 MHz, support of Trimble, Pacific Crest, and SATEL radio protocols:		
	Transmit power	2 W	
	Range	3–5 km typical / 10 km optimal ¹⁴	
Cellular ¹⁵	Integrated, 3.5 G modem, HSDPA 7.2 Mbps (download), GPRS multi-slot class 12, EDGE multi-slot class 12, Penta-band UMTS/HSDPA (WCDMA/FDD) 800/850/900/1900/2100 MHz, Quad-band EGSM 850/900/1800/1900 MHz, GSM CSD, 3GPP LTE		
Bluetooth	Version 4.1 ¹⁶		
Wi-Fi	802.11 b,g, access point and client mode, WPA/WPA2/WEP64/WEP128 encryption		
I/O ports	Serial, USB, TCP/IP, IBSS/NTRIP, Bluetooth		
Data storage	6 GB internal memory		
Data format	CMR+, CMRx, RTCM 2.1, RTCM 2.3, RTCM 3.0, RTCM 3.1, RTCM 3.2 input and output 24 NMEA outputs, GSOF, RT17 and RT27 outputs, 1 PPS output		
WEBUI	22. rodiputo, door, 1117 dilutti 27 odiputo, 1111 ot		
WEBOI	Offers simple configuration, operation, status, and data to	ransfer	
	Accessible via Wi-Fi, Serial, USB, and Bluetooth		
SUPPORTED CONTROLLERS & FIELD			
OUT ON ED CONTINUED AND ATTECH	Trimble TSC7, Trimble T10, Trimble T7, Android and iOS devices running supported apps		
	Trimble Access 2020.10 or later	O sept s see expression	
AUGMENTED REALITY			
MOGINICITIED REACHT	Supports outdoor augmented reality capabilities through Trimble SiteVision running on the Trimble TSC7 controller		
CERTIFICATIONS			
	FCC Part 15 (Class B device), 24, 32; CE Mark; RCM; PTC	RB; BT SIG	

